
The FX3000 Flexible Current Probe offers 10 to 3000 Amp AC current measurements.

Specifications

- 10 to 3000 A_{RMS} AC Current measurement

Accuracy

- 2% of reading +/- 0.2 amps (for currents below 400 A_{RMS}) or +/- 2 Arms (for currents from 400-3000 A_{RMS})

Dimensions

- 24.0 inch Flexible Circumference
- Inside diameter of 7.5 inches
- Outside measurement of 24.0 x .85 inches



Power Requirements

The probe connects directly into PowerSight®. No additional batteries are required.

Availability

The FX3000 is available for immediate purchase from Summit Technology Inc. To order, specify **FX3000**.

PowerSight® Energy Analyzer is manufactured in the USA and sold by Summit Technology, Inc.

For more information on our products contact:

Summit Technology Inc.
2246 Monument Blvd.
Pleasant Hill, CA 94523-3453

Voice: 1-925-944-1212
Fax: 1-925-521-1220
Email: sales@powersight.com