



2000 Amp DC / 1500 Amp AC Current Probe

Order Number:
[DC2000]

The PowerSight DC2000 Current Probe offers 1500 Amp AC current measurement as well as 2000 Amp DC current measurement.

Specifications

- 10 to 2000 Amps DC Current measurement
- 10 to 1500 Amps AC Current measurement
- No batteries required, power is supplied by attached PowerSight meter

Accuracy

- +/- 1 amp +/- 3% from 10 to 1500 amps AC/DC
- +/- 1 amp +/- 3% from 10 to 2000 amps DC

Dimensions

- 13.23 x 5.4 x 1.65 inches
- The DC2000 has an inside diameter of 3.27 inch and can clamp around one 3.27" cable or two 2.27" cables
- Cable length is 2 meters (6.5 feet).



Pricing and Availability

The DC2000 is available. To order, specify **DC2000**.

PowerSight® products are manufactured in the USA and sold by Summit Technology, Inc.

For more information on our products contact:

Summit Technology Inc.
2717 N. Main St., Suite 15
Walnut Creek, CA 94597-2747

Voice: 1-925-944-1212
Fax: 1-925-944-7126
Email: sales@powersight.com

PowerSight® is a trademark of Summit Technology. Prices and specifications are subject to change without notice.